

Supported Cisco Unified Communications Manager Releases by Server

Server Models Supported by Cisco Unified Communications Manager Releases

When upgrading, use Table 1 to confirm that your server model is supported by the target Cisco® Unified Communications Manager (previously known as Cisco Unified CallManager) release. If your server is not supported, you must replace it with a newer server if you want to run the target Cisco Unified Communications Manager release.

Table 1. Supported Server Models for Cisco CallManager 3.3 through Cisco Unified Communications Manager 4.3

Part Number	CPU Speed	Cisco CallManager 3.3	Cisco Unified CallManager 4.0*	Cisco Unified CallManager 4.1*	Cisco Unified CallManager 4.2*	Cisco Unified Communications Manager 4.3
MCS-7815-1000-HW	1.0 GHz	X	X	X	X	
MCS-7815I-2.0-EVV1	2.0 GHz	X	X	X	X	
MCS-7815I-3.0-IPC1	3.06 GHz	X	X	X	X	X
MCS-7815I-3.0-IPC2	3.06 GHz	X	X	X	X	X
MCS-7815-I2-IPC1	3.06 GHz	X	X	X	X	X
MCS-7815-I1-IPC2	3.06 GHz	X	X	X	X	X
MCS-7815-I1-IPC3	3.06 GHz	X	X	X	X	X
MCS-7815-I1-IPC4	3.06 GHz	X	X	X	X	X
MCS-7815-I2-IPC1	2.8 GHz	X	X	X	X	X
MCS7815I1-K9-CM50	3.06 GHz					
MCS7815I2-K9-CMA1	2.8 GHz					
MCS-7816-H3-IPC1**	3.2 GHz					X
MCS-7816-I3-IPC1**	3.2 GHz					X
MCS7816H3-K9-CMA2	3.2 GHz					
MCS7816H3-K9-CMB1	3.2 GHz					
MCS7816I3-K9-CMA2	3.2 GHz					
MCS7816I3-K9-CMB1	3.2 GHz					
MCS-7820-HW	500 MHz	X				
MCS-7822-HW	550 MHz	X				
MCS-7825-800	800 MHz	X	X	X		
MCS-7825-1133-HW	1.13 GHz	X	X	X	X	
MCS-7825H-2.2-EVV1	2.26 GHz	X	X	X	X	X
MCS-7825H-3.0-IPC1	3.06 GHz	X	X	X	X	X
MCS-7825I-3.0-IPC1	3.06 GHz	X	X	X	X	X
MCS-7825-H1-IPC1	3.4 GHz	X	X	X	X	X
MCS-7825-H2-IPC1	2.8 GHz	X	X	X	X	X
MCS-7825-H2-IPC2**	3.4 GHz	X	X	X	X	X
MCS-7825-H3-IPC1**	2.13 GHz	X	X	X	X	X
MCS-7825-I1-IPC1	3.4 GHz	X	X	X	X	X

MCS-7825-I2-IPC1	2.8 GHz	X	X	X	X	X
MCS-7825-I2-IPC2**	3.4 GHz	X	X	X	X	X
MCS-7825-I3-IPC1**	2.13 GHz	X	X	X	X	X
MCS7825H1-K9-CM50	3.4 GHz					
MCS7825H2-K9-CMA1	2.8 GHz					
MCS7825H2-K9-CMA1	3.4 GHz					
MCS7825H2-K9-CMA2	2.8 GHz					
MCS7825H2-K9-CMA2	3.4 GHz					
MCS7825H3-K9-CMA2	2.13 GHz					
MCS7825H3-K9-CMB1	2.13 GHz					
MCS7825I1-K9-CM50	3.4 GHz					
MCS7825I2-K9-CMA1	2.8 GHz					
MCS7825I2-K9-CMA1	3.4 GHz					
MCS7825I2-K9-CMA2	2.8 GHz					
MCS7825I2-K9-CMA2	3.4 GHz					
MCS7825I3-K9-CMA2	2.13 GHz					
MCS7825I3-K9-CMB1	2.13 GHz					
MCS7828H3-K9-CMB1	2.13 GHz					
MCS7828I3-K9-CMB1	2.13 GHz					
ICS-7750	700 MHz	X	X			
MCS-7830	500 MHz	X				
MCS-7835-NTD	733 MHz	X	X	X		
MCS-7835-TD	733 MHz	X	X	X		
MCS-7835-1000-NTD	1.0 GHz	X	X	X		
MCS-7835-1000-TD	1.0 GHz	X	X	X		
MCS-7835-1266-NTD	1.26 GHz	X	X	X	X	
MCS-7835-1266-TD	1.26 GHz	X	X	X	X	
MCS-7835H-2.4-EVV1	2.4 GHz	X	X	X	X	X
MCS-7835I-2.4-EVV1	2.4 GHz	X	X	X	X	X
MCS-7835H-3.0-IPC1	3.06 GHz	X	X	X	X	X
MCS-7835I-3.0-IPC1	3.06 GHz	X	X	X	X	X
MCS-7835-H1-IPC1	3.4 GHz	X	X	X	X	X
MCS-7835-H2-IPC1	2.33 GHz	X	X	X	X	X
MCS-7835-I1-IPC1	3.4 GHz	X	X	X	X	X
MCS-7835-I2-IPC1	2.33 GHz	X	X	X	X	X
MCS7835H1-K9-CM50	3.4 GHz					
MCS7835H2-K9-CMA1	2.33 GHz					
MCS7835H2-K9-CMA2	2.33 GHz					
MCS7835I1-K9-CM50	3.4 GHz					
MCS7835I2-K9-CMA1	2.33 GHz					
MCS7835I2-K9-CMA2	2.33 GHz					
MCS-7845-1400-HW	1.4 GHz	X	X	X	X	
MCS-7845H-2.4-EVV1	2.4 GHz	X	X	X	X	X
MCS-7845H-3.0-IPC1	3.06 GHz	X	X	X	X	X
MCS-7845I-3.0-IPC1	3.06 GHz	X	X	X	X	X
MCS-7845-H1-IPC1	3.4 GHz	X	X	X	X	X

MCS-7845-H2-IPC1	2.33 GHz	X	X	X	X	X
MCS-7845-I1-IPC1	3.4 GHz	X	X	X	X	X
MCS-7845-I2-IPC1	2.33 GHz	X	X	X	X	X
MCS7845H1-K9-CM50	3.4 GHz					
MCS7845H2-K9-CMA1	2.33 GHz					
MCS7845H2-K9-CMA2	2.33 GHz					
MCS7845I1-K9-CM50	3.4 GHz					
MCS7845I2-K9-CMA1	2.33 GHz					
MCS7845I2-K9-CMA2	2.33 GHz					
HP DL320	800 MHz	X	X			
HP DL320	1.13 GHz	X	X	X	X	
HP DL320-G2	2.26 GHz	X	X	X	X	X
HP DL320-G2	3.06 GHz	X	X	X	X	X
HP DL320-G3	3.4 GHz	X	X	X	X	X
HP DL320-G4	2.8 GHz	X	X	X	X	X
HP DL320-G4**	3.4 GHz	X	X	X	X	X
HP DL380 (1 CPU)	1.0 GHz	X	X			
HP DL380-G2 (1 CPU)	1.26 GHz	X	X	X	X	
HP DL380-G3 (1 CPU)	2.4 GHz	X	X	X	X	X
HP DL380-G3 (1 CPU)	3.06 GHz	X	X	X	X	X
HP DL380-G4 (1 CPU)	3.4 GHz	X	X	X	X	X
HP DL380-G5 (1 CPU)	2.33 GHz	X	X	X	X	X
HP DL380-G2 (2 CPUs)	1.4 GHz	X	X	X	X	
HP DL380-G3 (2 CPUs)	2.4 GHz	X	X	X	X	X
HP DL380-G3 (2 CPUs)	3.06 GHz	X	X	X	X	X
HP DL380-G4 (2 CPUs)	3.4 GHz	X	X	X	X	X
HP DL380-G5 (2 CPUs)	2.33 GHz	X	X	X	X	X
IBM x306	3.06 GHz	X	X	X	X	X
IBM x306	3.4 GHz	X	X	X	X	X
IBM x306m	2.8 GHz	X	X	X	X	X
IBM x306m**	3.4 GHz	X	X	X	X	X
IBM x330	800 MHz	X	X	X		
IBM x330	866 MHz	X	X	X		
IBM x330	933 MHz	X	X	X		
IBM x330	1.0 GHz	X	X	X		
IBM x330	1.2 GHz	X	X	X		
IBM x340	1.0 GHz	X	X	X		
IBM x342	1.2 GHz	X	X	X		
IBM x345 (1 CPU)	2.4 GHz	X	X	X	X	X
IBM x345 (1 CPU)	3.06 GHz	X	X	X	X	X
IBM x346 (1 CPU)	3.4 GHz	X	X	X	X	X
IBM x3650 (1 CPU)**	2.33 GHz	X	X	X	X	X
IBM x345 (2 CPUs)	3.06 GHz	X	X	X	X	X

IBM x346 (2 CPUs)	3.4 GHz	X	X	X	X	X
IBM x3650 (2 CPU)**	2.33 GHz	X	X	X	X	X

*Servers running Cisco Unified CallManager 4.0 and higher require a minimum of 2 GB of memory for Cisco MCS 7815, 7825, and 7835 Media Convergence Servers (MCSs) and 4 GB of memory for Cisco MCS 7845. For more information refer to http://www.cisco.com/en/US/products/sw/voicesw/ps556/prod_bulletin0900aecd80284099.html.

**These servers cannot upgrade to Cisco Unified CallManager 5.0. If customers want to upgrade to Cisco Unified CallManager 5.0, they must upgrade to Cisco Unified Communications Manager 5.1 or higher.

For information about specific configuration details for the supported Hewlett-Packard and IBM servers, visit <http://www.cisco.com/go/swonly>.

Table 2 lists supported server models for Cisco Unified CallManager 5.0 through Cisco Unified Communications Manager 6.0.

Table 2. Supported Server Models for Cisco Unified CallManager 5.0 through Cisco Unified Communications Manager 6.0

Part Number	CPU Speed	Cisco Unified CallManager 5.0**	Cisco Unified Communications Manager 5.1**	Cisco Unified Communications Manager 6.0	Cisco Unified Communications Manager 6.1
MCS-7815-1000-HW	1.0 GHz				
MCS-7815I-2.0-EVV1	2.0 GHz				
MCS-7815I-3.0-IPC1	3.06 GHz	X	X	X	X
MCS-7815I-3.0-IPC2	3.06 GHz	X	X	X	X
MCS-7815-I2-IPC1	3.06 GHz	X	X	X	X
MCS-7815-I1-IPC2	3.06 GHz	X	X	X	X
MCS-7815-I1-IPC3	3.06 GHz	X	X	X	X
MCS-7815-I1-IPC4	3.06 GHz	X	X	X	X
MCS-7815-I2-IPC1	2.8 GHz	X	X	X	X
MCS7815I1-K9-CM50	3.06 GHz	X	X	X	X
MCS7815I2-K9-CMA1	2.8 GHz	X	X	X	X
MCS-7816-H3-IPC1*	3.2 GHz		X	X	X
MCS-7816-I3-IPC1*	3.2 GHz		X	X	X
MCS7816H3-K9-CMA2	3.2 GHz		X	X	X
MCS7816H3-K9-CMB1	3.2 GHz		X	X	X
MCS7816I3-K9-CMA2	3.2 GHz		X	X	X
MCS7816I3-K9-CMB1	3.2 GHz				
MCS-7820-HW	500 MHz				
MCS-7822-HW	550 MHz				
MCS-7825-800	800 MHz				
MCS-7825-1133-HW	1.13 GHz				
MCS-7825H-2.2-EVV1	2.26 GHz	X	X	X	X
MCS-7825H-3.0-IPC1	3.06 GHz	X	X	X	X
MCS-7825I-3.0-IPC1	3.06 GHz	X	X	X	X
MCS-7825-H1-IPC1	3.4 GHz	X	X	X	X
MCS-7825-H2-IPC1	2.8 GHz	X	X	X	X
MCS-7825-H2-IPC2*	3.4 GHz		X	X	X
MCS-7825-H3-IPC1*	2.13 GHz		X	X	X
MCS-7825-I1-IPC1	3.4 GHz	X	X	X	X
MCS-7825-I2-IPC1	2.8 GHz	X	X	X	X

MCS-7825-I2-IPC2*	3.4 GHz		X	X	X
MCS-7825-I3-IPC1*	2.13 GHz		X	X	X
MCS7825H1-K9-CM50	3.4 GHz	X	X	X	X
MCS7825H2-K9-CMA1	2.8 GHz	X	X	X	X
MCS7825H2-K9-CMA1	3.4 GHz		X	X	X
MCS7825H2-K9-CMA2	2.8 GHz		X	X	X
MCS7825H2-K9-CMA1	3.4 GHz		X	X	X
MCS7825H3-K9-CMA2	2.13 GHz		X	X	X
MCS7825H3-K9-CMB1	2.13 GHz				
MCS7825I1-K9-CM50	3.4 GHz	X	X	X	X
MCS7825I2-K9-CMA1	2.8 GHz	X	X	X	X
MCS7825I2-K9-CMA1	3.4 GHz		X	X	X
MCS7825I2-K9-CMA2	2.8 GHz		X	X	X
MCS7825I2-K9-CMA2	3.4 GHz		X	X	X
MCS7825I3-K9-CMA2	2.13 GHz		X	X	X
MCS7825I3-K9-CMB1	2.13 GHz		X	X	X
MCS7828H3-K9-CMB1**	2.13 GHz			X	X
MCS7828I3-K9-CMB1**	2.13 GHz			X	X
ICS-7750	700 MHz				
MCS-7830	500 MHz				
MCS-7835-NTD	733 MHz				
MCS-7835-TD	733 MHz				
MCS-7835-1000-NTD	1.0 GHz				
MCS-7835-1000-TD	1.0 GHz				
MCS-7835-1266-NTD	1.26 GHz				
MCS-7835-1266-TD	1.26 GHz				
MCS-7835H-2.4-EVV1	2.4 GHz	X	X	X	X
MCS-7835I-2.4-EVV1	2.4 GHz	X	X	X	X
MCS-7835H-3.0-IPC1	3.06 GHz	X	X	X	X
MCS-7835I-3.0-IPC1	3.06 GHz	X	X	X	X
MCS-7835-H1-IPC1	3.4 GHz	X	X	X	X
MCS-7835-H2-IPC1*	2.33 GHz		X	X	X
MCS-7835-I1-IPC1	3.4 GHz	X	X	X	X
MCS-7835-I2-IPC1*	2.33 GHz		X	X	X
MCS7835H1-K9-CM50	3.4 GHz	X	X	X	X
MCS7835H2-K9-CMA1	2.33 GHz		X	X	X
MCS7835H2-K9-CMA2	2.33 GHz		X	X	X
MCS7835I1-K9-CM50	3.4 GHz	X	X	X	X
MCS7835I2-K9-CMA1	2.33 GHz		X	X	X
MCS7835I2-K9-CMA2	2.33 GHz		X	X	X
MCS-7845-1400-HW	1.4 GHz				
MCS-7845H-2.4-EVV1	2.4 GHz	X	X	X	X
MCS-7845H-3.0-IPC1	3.06 GHz	X	X	X	X
MCS-7845I-3.0-IPC1	3.06 GHz	X	X	X	X
MCS-7845-H1-IPC1	3.4 GHz	X	X	X	X
MCS-7845-H2-IPC1*	2.33 GHz		X	X	X

MCS-7845-I1-IPC1	3.4 GHz	X	X	X	X
MCS-7845-I2-IPC1*	2.33 GHz		X	X	X
MCS7845H1-K9-CM50	3.4 GHz	X	X	X	X
MCS7845H2-K9-CMA1	2.33 GHz		X	X	X
MCS7845H2-K9-CMA2	2.33 GHz		X	X	X
MCS7845I1-K9-CM50	3.4 GHz	X	X	X	X
MCS7845I2-K9-CMA1	2.33 GHz		X	X	X
MCS7845I2-K9-CMA2	2.33 GHz		X	X	X
HP DL320	800 MHz				
HP DL320	1.13 GHz				
HP DL320-G2	2.26 GHz	X	X	X	X
HP DL320-G2	3.06 GHz	X	X	X	X
HP DL320-G3	3.4 GHz	X	X	X	X
HP DL320-G4	2.8 GHz	X	X	X	X
HP DL320-G4*	3.4 GHz		X	X	X
HP DL320-G5*	2.13 GHz		X	X	X
HP DL380 (1 CPU)	1.0 GHz				
HP DL380-G2 (1 CPU)	1.26 GHz				
HP DL380-G3 (1 CPU)	2.4 GHz	X	X	X	X
HP DL380-G3 (1 CPU)	3.06 GHz	X	X	X	X
HP DL380-G4 (1 CPU)	3.4 GHz	X	X	X	X
HP DL380-G5 (1 CPU)*	2.33 GHz		X	X	X
HP DL380-G2 (2 CPUs)	1.4 GHz				
HP DL380-G3 (2 CPUs)	2.4 GHz	X	X	X	X
HP DL380-G3 (2 CPUs)	3.06 GHz	X	X	X	X
HP DL380-G4 (2 CPUs)	3.4 GHz	X	X	X	X
HP DL380-G5 (2 CPUs)*	2.33 GHz		X	X	X
IBM x306	3.06 GHz	X	X	X	X
IBM x306	3.4 GHz	X	X	X	X
IBM x306m	2.8 GHz	X	X	X	X
IBM x306m*	3.4 GHz		X	X	X
IBM x3250*	2.13 GHz		X	X	X
IBM x330	800 MHz				
IBM x330	866 MHz				
IBM x330	933 MHz				
IBM x330	1.0 GHz				
IBM x330	1.2 GHz				
IBM x340	1.0 GHz				
IBM x342	1.2 GHz				
IBM x345 (1 CPU)	2.4 GHz	X	X	X	X
IBM x345 (1 CPU)	3.06 GHz	X	X	X	X
IBM x346 (1 CPU)	3.4 GHz	X	X	X	X
IBM x3650 (1 CPU)*	2.33 GHz		X	X	X
IBM x345 (2 CPUs)	3.06 GHz	X	X	X	X

IBM x346 (2 CPUs)	3.4 GHz	X	X	X	X
IBM x3650 (2 CPUs)*	2.33 GHz		X	X	X

*These servers cannot upgrade to Cisco Unified CallManager 5.0. If customers want to upgrade to Cisco Unified CallManager 5.0, they must upgrade to Cisco Unified Communications Manager 5.1.

**These servers operate as coresident servers running Cisco Unified Communications Manager 6.0 and Cisco Unity® Connection 2.0 simultaneously. They do not support the running of just Cisco Unified Communications Manager 6.0.

For information about specific configuration details for the supported Hewlett-Packard and IBM servers, visit <http://www.cisco.com/go/swonly>.

For information about upgrading to a specific Cisco Unified Communications Manager release or replacing an existing server, please contact your local systems engineer.



Americas Headquarters
 Cisco Systems, Inc.
 170 West Tasman Drive
 San Jose, CA 95134-1706
 USA
www.cisco.com
 Tel: 408 526-4000
 800 553-NETS (6387)
 Fax: 408 527-0883

Asia Pacific Headquarters
 Cisco Systems (USA) Pte. Ltd.
 168 Robinson Road
 #28-01 Capital Tower
 Singapore 068912
www.cisco.com
 Tel: +65 6317 7777
 Fax: +65 6317 7799

Europe Headquarters
 Cisco Systems International BV
 Haarlerbergpark
 Haarlerbergweg 13-19
 1101 CH Amsterdam
 The Netherlands
www-europe.cisco.com
 Tel: +31 0 800 020 0791
 Fax: +31 0 20 357 1100

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.

CCVP, the Cisco logo, and Welcome to the Human Network are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn is a service mark of Cisco Systems, Inc.; and Access Registrar, Aironet, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, IP/TV, IQ Expertise, the iQ logo, iQ Net Readiness Scorecard, iQuick Study, LightStream, Linksys, MeetingPlace, MGX, Networkers, Networking Academy, Network Registrar, PIX, ProConnect, ScriptShare, SMARTnet, StackWise, The Fastest Way to Increase Your Internet Quotient, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0711R)